

## Burghiu magnetic 1000W 32mm METABO MAG 32

Numar articol: **600635500**

Cod de bare: **4007430238207**

✓ -



### TECHNICAL FEATURES

Parameter	Measure Unit	Value
Inaltimea saniei in cea mai de jos pozitie (mm)	mm	343
Lungime cablu (m)	m	5
Cuplu maxim (Nm)	Nm	50
Cuplu minim (Nm)	Nm	50
Adancime maxima de gaurire (mm)	mm	50
Turatie maxima in gol (min-1)	min-1	0 - 700
Turatie maxima in sarcina (min-1)	min-1	0 - 450
Gaurire maxima Ø in otel (mm)	mm	32
Diametru maxim de gaurire (mm)	mm	13
Fora magnetica maxima (N)	N	12250
Adancimea maxima de alimentare (mm)	mm	160
Putere nominala de intrare (W)	W	1000
Tensiune nominala (V)	V	230
Capacitatea mandrinei (mm)	mm	13 - 32
Putere de iesire (W)	W	520
Inapoi		NU
Control cuplu		NU
Viteze		1
Tip motor electric		Marathon
Tensiune nominala		Cu fir - retea electrica
Funcție de impact		NU
Dimensiunea bazei magnetice (mm)	mm	90x189
Filet ax		Weldon shank 19
Prindere (Inch)		Weldon shank 19



EUROMASTER SRL, 075100 Romania, Drumul Garii  
Otopeni, nr.6, Oras Otopeni, Jud. Ilfov  
+ 40 21 351 01 06  
marketing@euromasters.ro

